



直流电容式接近传感器(M12)

直径	M12			M12		
埋入安装/露出安装	埋入安装/露出安装			埋入安装/露出安装		
感应距离 (Sn: mm)	1-3mm 可调 / 1-6mm 可调			1-3mm 可调 / 1-6mm 可调		
外壳材质	黄铜镀镍			PBT 塑料		
有无LED	有LED			有LED		
图片						
工作电压	10-30VDC			10-30VDC		
涟波	<10%			<10%		
无负载电流	<10mA			<10mA		
最大负载电流	200mA			200mA		
漏电流	<0.01mA			<0.01mA		
电压降	< 2VDC			< 2VDC		
开关频率	100HZ			100HZ		
开关磁滞	<15%(sr)			<15%(sr)		
重复精度	<5%(sr)			<5%(sr)		
防护等级	IP67			IP67		
工作环境温度	-25 ℃ - +70 ℃			-25 ℃ - +70 ℃		
温度漂移	<10%(sr)			<10%(sr)		
短路保护	有			有		
过载电流保护点	220mA			220mA		
感应面材质	POM			PBT		
DC 三线式 10-30V NPN 常开	C1B1-M1203N-OEA4	B1-M2-M1206N-OEA4	31	C1P1-M1203N-OEA4	C1P2-M1206N-OEA4	31
DC 三线式 10-30V NPN 常闭	C1B1-M1203N-CEA4	B1-M2-M1206N-CEA4	32	C1P1-M1203N-CEA4	C1P2-M1206N-CEA4	32
DC 三线式 10-30V PNP 常开	C1B1-M1203P-OEA4	B1-M2-M1206P-OEA4	33	C1P1-M1203P-OEA4	C1P2-M1206P-OEA4	33
DC 三线式 10-30V PNP 常闭	C1B1-M1203P-CEA4	B1-M2-M1206P-CEA4	34	C1P1-M1203P-CEA4	C1P2-M1206P-CEA4	34
DC 四线式 10-30V PNP 输出常开常闭可转换	-	-	-	-	-	-
DC 四线式 10-30V NPN 输出常开常闭可转换	-	-	-	-	-	-
DC 两线式 10-60V 常开	-	-	-	-	-	-
DC 两线式 10-60V 常闭	-	-	-	-	-	-
DC 三线式 10-55v NPN 常开	-	-	-	-	-	-
DC 三线式 10-55v NPN 常闭	-	-	-	-	-	-
DC 三线式 10-55v PNP 常开	-	-	-	-	-	-
DC 三线式 10-55v PNP 常闭	-	-	-	-	-	-
DC 三线式 5-36V PNP 常闭	-	-	-	-	-	-
DC 三线式 5-36V PNP 常开	-	-	-	-	-	-
DC 三线式 5-36V NPN 常闭	-	-	-	-	-	-
DC 三线式 5-36V NPN 常开	-	-	-	-	-	-
DC 四线式 5-36V PNP 输出常开常闭可转换	-	-	-	-	-	-
DC 四线式 5-36V NPN 输出常开常闭可转换	-	-	-	-	-	-
接线图编号						
尺寸 (单位: mm)						
电线 2M (PVC)	-			-		
重量	约30克			约14克		

本公司注重产品质量改善, 有关修改恕不另行通知。

电话: +86-755-2646 7962

传真: +86-755-2646 7925

MSN: dfan852@hotmail.com

网站: www.mountiger.com

电邮: sales@mountiger.com

QQ: 873764592

Mountiger 盟泰格
Sensing the future 感应未来