







DC INDUCTIVE PROXIMITY RING SWITCH(15mm)

Diameter of Ring	15mm		15mm	
Shielded/non-Shielded	Non-Shielded		Non-Shielded	
Switching Distance, Sn mm	20mm		20mm	
Housing Material	PBT		PBT	
With LED/Without LED	With LED		With LED	
Picture				
Operating Voltage and Ripple	10-30VDC(Ripple<10%)		10-60VDC(Ripple<10%)	
Mini time Between Targets	-		-	
No Load Current	≤ 15mA		≤ 1.8mA	
Max. Load Current	200mA		100mA	
Leakge Current	≤ 10μA		≤ 1.2mA	
Surge Current	-		-	
Mini. Load Current	-		3mA	
Voltage Drop	≤ 1.5V at 200mA		≤ 6V at 100mA	
Switching Frequency	1.5KHz		1.5KHz	
Pulse Duration	-		-	
Switching Hysteresis	<15%(Sr)		<15%(Sr)	
Repeat Accuracy	<2.0%(Sr)		<2.0%(Sr)	
Protection Category	IP67		IP67	
Operating Temperature	-25 °C - +70 °C		-25 °C - +70 °C	
Temperature Drift	<10%(Sr)		<10%(Sr)	
Min. Target	Diameter 3mm, Length 6mm		Diameter 3mm, Length 6mm	
Reverse Polarity Protection	YES		YES	
Short Circuit Protection	YES		YES	
Overload Trip Point	220-280mA		120-150mA	
EMC	RFI>3V/M; EFT>1KV; ESD>4KV(contact)		RFI>3V/M; EFT>1KV; ESD>4KV(contact)	
Shock/Vibration	IEC60947-5-2 Part 7.4.1 and Part 7.4.2		IEC60947-5-2 Part 7.4.1 and Part 7.4.2	
DC 3 wire 10-30V NPN N.O.	D1P2-R1520N-O3A2	1	-	
DC 3 wire 10-30V NPN N.C.	D1P2-R1520N-C3A2	2	-	
DC 3 wire 10-30V PNP N.O.	D1P2-R1520P-O3A2	3	-	
DC 3 wire 10-30V PNP N.C.	D1P2-R1520P-C3A2	4	-	
DC 4 wire 10-30V Changeover PNP (N.O. & N.C.)	D1P2-R1520P-S4A2	6	-	
DC 4 wire 10-30V Changeover NPN (N.O. & N.C.)	D1P2-R1520N-S4A2	5	-	
DC 2 wire 10-60V N.O.	-		D4P2-R1520C-O2A2	7
DC 2 wire 10-60V N.C.	-		D4P2-R1520C-C2A2	8
NAMUR	-		-	
	-		-	
	-		-	
	-		-	
	-		-	
	-		-	
	-		-	
	-		-	
Wiring diagram number				
Dimensions (unit: mm)				
Cable 2M (PVC)	4φ 3x0.15		4φ 2x0.15	
Weight	approx.95g		approx.95g	

Subject to modifications without notice

Tel: +86-755-2646 7962

Fax: +86-755-2646 7925

MSN: dfan852@hotmail.com

Web: www.mountiger.com

E-mail: sales@mountiger.com

QQ: 873764592

